

PARIS DOOR CHIME KIT

Complete Door Chime Kit with traditional Ding Dong chime and red LED power indicator. Simple to install and supplied with fixing screws and 2 metres of cable.

Fitting instructions

Chime unit

1. Select a suitable location to mount the Chime Unit near the door, ensuring the 2 metre cable will reach the required location for the Bell Push.
2. Screw the domed headed screw into the wall leaving the head protruding.
3. Slide the Chime Unit onto the screw using the hole on the back, located above the battery compartment.

Bell push

1. Select a suitable flat location on the doorframe and drill a hole through the frame large enough to feed the wire through.
2. Feed the wire that is attached to the Chime Unit through the hole you have drilled in the doorframe.
3. Remove the Bell Push cover by inserting a small screwdriver into the slot at the bottom and twisting. Line up the Bell Push and feed the wire through the square hole at the top.
4. Mount the Bell Push using the two countersunk screws supplied.
5. If necessary cut the cable to the correct length and split the two wires. Trim back approximately 10mm of the insulation to expose the wire, loosen one of the two terminal screws and wrap one of the exposed wires around the screw; tighten (do not overtighten) the screw to ensure the wire makes a good connection between the screw and the copper contact point. Repeat with the other wire.
6. Replace the Bell Push cover.

Battery installation

Remove the battery compartment cover and insert 3 x AA alkaline batteries (not supplied) observing the battery polarity markings.

Your chime is now ready for use.



This product uses 3 x 'AA' alkaline batteries. They should be removed prior to disposal of the Chime Unit.

Help the environment by disposing of your product and batteries responsibly.

The wheeled bin symbols indicate the product and batteries must not be disposed of in the domestic waste as they contain substances which can be damaging to the environment and health.

Please use designated collection points or recycling facilities when disposing of the item or batteries.

More information can be found on: www.recycle-more.co.uk; www.recyclenow.com

Screws and wall plugs supplied – please note they are packed inside the battery compartment.



Uni-Com (Global) Ltd



PLEASE RECYCLE
WHERE FACILITIES EXIST

1 & 2 Enterprise Way
Edenbridge, Kent TN8 6EW

Made in China

© 2008 Uni-Com (Global) Ltd. All rights reserved
For more information visit www.uni-com.uk.com



Product Code: 54191